



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR GRID-CONNECTED POWER CONDITIONING  
UNITS**

PS 439-1752

REV. No. 00

PAGE 1 OF 15

**COPY RIGHT AND CONFIDENTIAL**

The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

**Technical specification  
for  
Supply, installation and commissioning of  
3-phase Grid-connected Power conditioning units  
of 2.5MW outdoor type inverter (IP65 & protection class II or higher)**

**Changes :**

1. NO of AC outputs : There will be 5 runs of 1C x 630 sqmm cable per phase ( clause no 4.9.2)
2. NO of DC inputs : there will be 10 inputs in DC SIDE (clause 4.8.1)
3. IEC 60721-3-3 CERTIFICATION is not mandatory (clause4.1.2)

**R00 dated  
20.09.2019**

**Approved: BHAGYASHREE S N**

**Prepared  
PHALGUNI SAHOO**

**Issued  
SC&PV-Engg**

**Date  
20.09.19**



PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS

PS 439-1752

REV. No. 00

PAGE 2 OF 14

COPY RIGHT AND CONFIDENTIAL

The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

**INTRODUCTION:**

This technical specification provides details of supply of Outdoor for 3-phase Grid-connected Power Conditioning Units (PCU). The scope also includes commissioning of the supplied units at the project site for synchronizing the generated ac power with LV side of a transformer that connects to 33kV grid on HV side.

**1.0 Scope of supply**

SL No	Item Description	Qty
1.1	Supply of : outdoor type inverter (IP65 & protection class II or higher) a) 2.5 MW outdoor inverter consisting of 3-phase, Grid-connected Power Conditioning Unit (PCU) of 1500V rating and suitable power rating along with other auxiliary items. Outdoor type inverter shall be minimum IP65 protection for Power Electronics & IP54 for Other parts .	70 sets
1.2	<b>Supply of Spares</b> for power conditioning units. List of items with quantity is as follows:  1) Control Cards for PCU ** Quantity = 1 set of each type  2) Fuses Quantity = 1 set of each type and rating  3) Surge Protection Device Quantity = 1 set of each type and rating  4) MCCBs, MCBs Quantity = 1 set of each type and rating  5) AC Contactor, DC Contactor, Air Circuit Breaker – 1 no each  <b>Notes:</b> (a) <b>1 SET = Total Quantity of items used in 1 PCU of rating 2.5MW .</b> (b) The above spare quantities are for contingency purposes over and above the warranty requirements. (c) Item-wise BOQ and break-up prices shall be provided in the offer. (d) Control cards for 1 PCU refers to all the electronics cards used in the PCU including main microprocessor cards, protection cards, I/O cards, gate driver cards and any other PCB used in the PCU not specifically indicated above.	2 sets (1set for each Project)



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 3 OF 14**

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

**1.3 Commissioning of PCUs along with Training at site.**

70 sets

BHEL scope of activities at site for installation and commissioning:

- (1) Movement and positioning of outdoor PCU panels at the earmarked position on the outdoor RCC platform.
- (2) Crimping the incoming (DC side) and outgoing (AC side) cables (BHEL supply) using the cable lugs provided by the vendor.
- (3) Connecting at the respective termination ends of the panels using the cable glands and fastening hardware (nuts, bolts, washers etc) provided by the vendor.

Vendor scope of activities at site for commissioning:

- (1) All the electrical checks that are required to confirm that solar DC parameters (current, voltage) are available at the DC input side of PCUs.
- (2) Service engineers shall be present at site during installation of PCUs, commissioning of solar power plant, providing all necessary guidance and support to achieve successful synchronization of PCU output with grid and also to trouble-shoot / resolve the technical problems associated with PCU. Commissioning / Service Engineer shall be from OEM.
- (3) Guidance and support to BHEL team, at the time of installation and commissioning of SCADA, in respect of connection of communication cables to PCUs and technical problems related to receiving data signals at SCADA station from PCUs.
- (4) Training: Vendor shall provide training at site to BHEL and customer's engineers during commissioning. Training shall cover various technical aspects such as functional/ operational features, trouble-shooting procedures, maintenance schedules, requirements, safety, emergency precautions etc. Both the theory and practical (hands on) training shall be covered.

Note: Supply and installation of integrated SCADA system for the overall power plant is within BHEL scope.

The lump-sum price shall include all the costs that will be incurred by the vendor towards commissioning including travel, boarding, lodging and any other contingency expenses.

**2.0 Warranty**

Vendor shall provide comprehensive warranty for 60 months from date of commissioning or 63 months from date of supply, whichever is earlier. Vendor shall enclose, along with technical bid, the complete scope, terms and conditions of the warranty.

During the warranty period, whenever a technical problem is encountered with the PCU, BHEL will report the same to the vendor. Vendor shall ensure that the problem is attended to by their service engineer within two days from the date of reporting.

**3.0 Technical Documents to be submitted along with offer**

1. Vendor has to enclose the deviation sheet clause wise separately in case any deviations are sought by the vendor. Absence of any deviation sheet shall be taken as compliance of BHEL specification in total without any deviation.
2. Product datasheet of the offered PCU model.



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 4 OF 14**

3. Overall General Arrangement of PCU including DC and AC Combiner Panels.
4. List of spares offered (with quantity) and without prices.
5. List of type tests /IEC certifications available along with test certificates. Supporting test reports shall be provided by vendor during detailed engineering.
6. Filled in format-A enclosed with this specification regarding manufacturing capacity and orders under execution.

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

**4.0 Technical specification of Power Conditioning Units**

**4.1 Basic requirements (PCU type, Standards, Technology, Interconnections, Interfaces etc)**

#	Parameter	BHEL specification
4.1.1	PCU type	<p>Grid-interactive.</p> <p>PCU shall remain connected to the grid as per Central Electricity Authority Technical (standards for connectivity to the grid) regulation 2007 with all latest amendments and its components shall be designed accordingly.</p> <p><b>Low power mode:</b></p> <p>The control system that continuously monitors the output of the solar PV plant until pre-set value is exceeded and begins to export power provided there is sufficient solar energy and the grid voltage and frequency are in the specified range.</p> <p>Further, the inverter shall be capable of operation under reduced power mode and shall not trip when the PV array output voltage is below MPPT range under high temperature conditions.</p> <p><b>Active MPPT mode (high power mode):</b></p> <p>When solar radiation increases further, PCU shall enter maximum power point tracking (MPPT) mode and adjust the voltage of the SPV array to maximize solar energy fed into the grid. When the solar radiation falls below threshold level, the PCU shall enter lower power mode.</p> <p><b>Sleep mode:</b></p> <p>Automatic 'sleep' mode shall be provided so that unnecessary losses are minimized at night. Vendor shall provide threshold DC voltage level / power level of the PCU as to when it shall enter into the sleep mode and back to low power mode and MPPT mode during detailed engineering for BHEL/customer approval.</p> <p><b>Low Voltage mode:</b></p> <p>The Inverter shall be capable of operating under reduced power mode and shall not trip when the PV array output is below MPPT range under high temperature conditions.</p>



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 5 OF 14**

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

4.1.2	Compliance with standards	<b>Sl.</b>	<b>Standard</b>	<b>Description</b>
		1	IEC 61683	Photovoltaic systems - Power conditioners – Procedure for measuring efficiency
		2	IEC 62109-1 & 2	Safety of power converters for use in photovoltaic power systems
		3	IEC 61000-6-2	Electromagnetic compatibility (EMC) - Part 6-2: Generic standards-Immunity Standard for industrial environments
		4	IEC 61000-6-4	Electromagnetic compatibility (EMC) - Part 6-4: Generic standards- Emission standard for industrial environments
		5	IEC 62116/ IEEE 1547/IEE 519 / UL 1741 / Equivalent EN/ BIS standard	Utility-interconnected photovoltaic inverters – Test procedure of islanding prevention measures, Anti Islanding
		6	IEC 62103/ IEC 62109-1 & 2	Photovoltaic (PV) systems - of the Characteristics utility interface
		7	IEC 60068-2/ IEC 62093	Environmental testing / MPPT
		9	<del>IEC 60721-3-3</del>	<del>Classification chemically active substance 3C2 &amp; 3S2</del>
8	Grid Connectivity - CEA Technical Standards for Connectivity to the Grid Regulations 2007 with latest amendment and latest CERC /GERC Regulations and Grid Codes - including LVRT requirement			
All the type test certificates as per the standards mentioned above shall be submitted for approval.				
4.1.3	Output transformer	PCU shall be of 'transformer-less' design.		
4.1.4	Maximum Power Point Tracking (MPPT)	MPPT shall be integrated in the power conditioning unit to maximize energy drawn from the solar PV array. The MPPT should be microprocessor based to minimize power losses. The details of working mechanism of MPPT shall be submitted during the detailed engineering. The operating voltage range of PCU and the MPPT shall be large enough such that it satisfactorily operates for PV modules exposed to the maximum ambient temperature of 50 deg C.  The MPPT unit shall confirm to IEC 62093 for design qualification.		
4.1.5	AC-DC conversion	3-phase Inverter stack		
4.1.6	Built-in support systems	PCU shall be provided with protection circuits, monitoring circuits, data logging & storage system, provisions to download data to PC/Laptop, MODBUS communication outputs for SCADA interface etc as per Cl. 4.7 of this specification.		
4.1.7	Heat exchangers	Vendor shall submit HVAC calculations during detailed engineering.		
4.1.8	DC input and AC	Input and output terminations together with cable glands, lugs, hardware shall be provided to match the connections using BHEL cables as specified under		



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 6 OF 14**

	output terminations	related clauses of this specification. Terminals should be shrouded.
4.1.9	Environment protection	All PCB cards shall be provided with suitable coating (epoxy etc) for protection.

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

**4.2 Technical parameters**

#	Technical parameter	BHEL specification
4.2.1	Output power rating	2500 kW minimum, 1500V (at 50 deg C ambient) – No derating upto 50degC
4.2.2	AC grid connection	3-phase
4.2.3	Output frequency	50 Hz +/- 5%
4.2.4	Nominal output voltage	Value to be indicated by vendor
4.2.5	Maximum DC input voltage (Max open circuit PV voltage)	1500 V DC
4.2.6	MPPT Range of control system	Range to be indicated by vendor.
4.2.7	DC side peak power	Vendor shall confirm that PCU is suitable for overloading of DC input power. Vendor to indicate the value in % . Minimum requirement is 40%
4.2.8	Max DC operating current	Value to be indicated by vendor.
4.2.9	Max AC output current	Value to be indicated by vendor corresponding to the rated output power of the PCU.
4.2.10	Power factor	Designed operation close to unity PF. Adjustable window 0.85 lead to 0.85 lag
4.2.11	Ambient temperature	0 to 50 deg C.
4.2.12	Relative Humidity	Upto 95% non-condensing
4.2.13	Protection class	IP 65 (Outdoor duty).
4.2.14	Grid Frequency tolerance	+/- 3 Hz
4.2.15	Grid Voltage tolerance	- 10% and + 10%
4.2.17	AC output THD limits	Less than 3% at rated pow earth leakage er
4.2.18	Maximum noise level	Value to be indicated by vendor



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 7 OF 14**

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

4.2.19	DC injection (as % of nominal load current)	DC injection shall be limited to 1% of the rated current of the inverter as per IEC 61727/IEE929/BDEW 2008.
4.2.20	Flicker	Shall be as per IEC 61000/IEE 519
4.2.21	Set point pre-selection for active power and VAR control	PCU shall be provided with all necessary features that will enable set point selection through SCADA.  For this PCU vendor shall furnish the Modbus mapping for the set points or suggest the possible method for selecting VAR control. Operator shall be able to limit the total power (Active and Reactive) injected in the grid through manual intervention as and when required in view of grid security.
4.2.22	Re-synchronization time	In case of grid failure, the PCU shall be re-synchronized with grid after revival of power supply. Vendor shall indicate the time taken by PCU to be re-synchronized after restoration of grid supply.
4.2.23	European Efficiency at 100% load	> 98%, measured as per IEC 61683 standard for measuring efficiency
4.2.24	Peak Efficiency	Inverter No Load / Full Load Loss Calculation must be submitted by the Bidder.
4.2.25	PCU availability	The up-time of Inverters should be of 99% in a year, in case of failing to achieve this due to failure of any component of inverter the vendor shall either replace the inverter or the component at their own cost
4.2.26	No load loss	No load loss shall be < 1% of rated power and maximum loss in sleep mode shall be less than 0.05%.
4.2.27	Voltage Ride Through	The PCU shall remain connected to the grid during temporary dip or rise in grid voltage as per the LVRT requirements of CEA Technical Standards for Connectivity to the Grid Regulations.  The PCU shall also be able to inject reactive power during the period of voltage dip.
4.2.28	Active power regulation	The PCU shall be able to limit the active power exported to the grid based on the set point provided through PCU front control panel. The PCU shall also be able to automatically the limit the active power after an increase in grid frequency above a pre-set value. The ramp rate shall be adjustable during operation and start-up after fault. The applicability of the requirement shall be as per CEA regulation and compliance.
4.2.29	Reactive power control	The PCU shall be able to inject /absorb reactive power to/ from the grid based on the set point provided through PCU front control panel. The same shall be performed automatically with adjustable ramp rate based on dynamic changes in grid voltage or reactive power reference
4.2.30	Enclosure	IP65 –outdoor IEC-60068-2 (environmental)

**4.3 Protection systems**



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 8 OF 14**

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

4.3.1	Protection systems for current, voltage, temperature, surges, ground faults, fan failure etc.  Fault indication shall be communicated to SCADA system	AC & DC over current
4.3.2		AC & DC short circuit
4.3.3		DC reverse polarity
4.3.4		Over temperature protection: Heat sink, Cabinet
4.3.5		Synchronization loss
4.3.6		Anti-islanding protection
4.3.7		EMI and RFI
4.3.8		Grid monitoring Protection against any sustained fault (lightning effect etc) in grid / feeder line.
4.3.9		Ground fault protection
4.3.10		Power regulation in the event of thermal overloading
4.3.11		SPD-based overvoltage protection on both DC and AC sides. SPD shall consist of MOV type arrestors. It shall have thermal disconnectors to interrupt surge current arising from internal / external faults. Type-II surge protective device (SPD) conforming to IEC 61643-11 shall be connected between positive/ negative bus and earth.
4.3.13	Fan failure – Alarm contact shall be provided for air flow loss / rise of temperature of cooling fan	

**4.4 DC, AC side load break disconnecting switch / breaker provisions**

4.4.1	DC side (Clause to be read in conjunction with clause 4.8.2)	Load break disconnecting mechanism required on DC side – DC current shall be communicated to SCADA (ALL SMB CURRENT SHALL BE MEASURED & DISPLAYED INDEPENDENTLY)
4.4.2	AC side	<p>(a) ACBs shall be provided on the AC output side.</p> <p>(b) Remote operating and controlling facility for Circuit Breaker from the Main Control Room shall be provided.</p> <p>(c) Aux contacts (ON/OFF feedback) from both ACB and DC Switch Disconnecter shall be made available at TB terminals to enable external wiring for SCADA monitoring purpose.</p> <p>(d) Surge protection device (3P) with suitable rating shall be provided at the input of the ACB.</p> <p>(e) Indication for grid side supply ON / OFF status shall be available on the Door Interface.</p> <p>(f) Interconnection between the ACB Panel and PCU supply/provision of cables / busbars as applicable shall be in the scope of the vendor.</p>



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 9 OF 14**

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

**4.5 Front panel display and control**

4.5.1	Front panel screen (LCD display, etc) with browsing / navigation provisions to 1) select display parameters 2) provide settings for various parameters	Instantaneous DC power input DC input voltage DC Current of each SMB (ALL SMB CURRENT SHALL BE MEASURED & DISPLAYED INDEPENDENTLY ) Total DC Current
4.5.2		Instantaneous active AC power output Instantaneous reactive AC power output AC voltage ( all the 3 phases and line) AC current ( all the 3 phases and line) Frequency Power Factor Energy (kWh) produced during entire day Total Energy (kWh) produced during its life
4.5.3		Faults
4.5.4		Other event logs
4.5.5		Other features as may be necessary for supervisory control and operation of the PCUs shall be provided.

**4.6 Data logging, storage, retrieval, downloading, uploading**

4.6.1	Provision of built-in systems for data logging, storage, retrieval, downloading, uploading etc.	Date-cum-time stamped logging of DC and AC side parameters (current, voltage, frequency, phase, power factor, power, export energy etc), faults and other events.
4.6.2		Data storage with retrieval features.
4.6.3		Provision of all necessary built-in systems, ports etc for downloading the data into a PC / Laptop etc that will be required for reporting, data analysis and trouble-shooting purposes.
4.6.4		Provision of all necessary built-in systems, ports etc for uploading of software etc that will be required for replacing, revising, upgrading the system.

**4.7 Provisions for SCADA interface**

4.7.1	SCADA interface requirement	Solar PV power plant will have an integrated SCADA, which is within BHEL scope, whereby all the PCUs will be integrated with other data systems such as solar array string monitoring, weather monitoring, HT side transformers / breakers monitoring, etc. Accordingly, PCU shall have necessary communication protocol and output ports to facilitate SCADA interface as per Clause 4.7.2. SCADA shall be OPC server based.
4.7.2	Communication protocol	Dedicated MODBUS TCP/IP on Ethernet Interface for networking with SCADA.



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 10 OF 14**

4.7.4	Parameters for SCADA	All DC and AC parameters (current, voltage, frequency, phase, power factor, power, export energy etc), grid data, temperature, faults, other event logs, date/time logs etc from each PCU will be required at SCADA control desk. PCU shall provide for this requirement. (ALL SMB CURRENT SHALL BE MEASURED & DISPLAYED INDEPENDENTLY )
4.7.5	Remote monitoring features	PCU shall have features to facilitate remote monitoring via telephone modem or mini web server.

**4.8 DC Inputs and termination details for 2500kW PCU.**

Vendor shall supply the PCU with the termination features on DC side as tabulated below. Detailed drawings of termination arrangements with bus bar particulars such as positions, dimensions, hole sizes, spacing between holes, support to bus bar, etc shall be submitted for BHEL approval.

4.8.1	DC input terminals	<b>10 input</b> Hence, a minimum of <b>10 DC input</b> terminals (each for DC +ve and -ve) shall be provided:-
4.8.2	Fuses / DC Ckt Breaker on DC input side	Fuse current rating <b>400A (min)</b> shall be provided on each positive DC input terminal.  Alternately, DC circuit breaker can also be provided as per design.  If DC breaker is provided for each input ,then DCswitch disconnect- or as per clause 4.4.1 is not mandatory
4.8.3	Max DC input current rating of PCU	Vendor shall indicate the rating. In addition, max rating of each individual DC input shall be indicated
4.8.4	DC cable entry into panel	Bottom entry. Cable supply is within BHEL scope.  1Cx400 sq-mm Aluminium, multi-strand, Al,armoured, XLPE insulation, PVC sheath cable will be used for each DC input. Exact size shall be provided during detailed engg.  DC termination shall be suitable for the above cable.
4.8.5	Gland plates	Drilled Gland plates shall be provided with holes to accommodate the cable glands.
4.8.6	Cable glands	Nickel plated brass, double compression type cable glands of reputed make (Make: Comet or any other reputed make) shall be provided by the vendor. To enable right selection of glands, final cable O.D will be provided by BHEL at the time of manufacturing.  Approval of make and type/size shall be taken from BHEL before procurement of glands. Part no. and qty shall be indicated in the

**COPY RIGHT AND CONFIDENTIAL**

The information on this document is the property of Bharat Heavy Electricals Limited. It must not be used directly or indirectly in anyway detrimental to the interest of the company.



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 11 OF 14**

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

		BOM. PCUs shall be supplied with all the glands fixed on the gland plates.
4.8.7	Cable lugs, plain washers, spring washers, bolts and nuts	Similarly, cable lugs, bolts, nuts & plain washers, Zinc coated spring washers shall be provided by the vendor. Make for lugs: Dowells or any other reputed make with CE/VDE/UL/CSA/BIS. Approval of make and type/size shall be taken from BHEL before procurement of lugs. Part no. and qty shall be indicated in the BOM. PCUs shall be supplied with all these items fixed on the bus bars at their respective positions. DC Cables in BHEL scope shall be Aluminium type. Suitable cable lugs in PCU vendor scope shall be based on the type of busbars being used in PCU : a) If Aluminium busbars used, aluminium lugs to be provided. c) If copper busbars used, Cu-Al Bi-metallic lugs or Aluminium Lugs with Bi-metallic strips/washers to be provided.
4.8.8	Bus bar design	Tinned Copper or Aluminium Busbars shall be provided.
4.8.9	In case of separate DC termination panel	(a) In case the DC terminations are not within the main PCU panel with the vendor design featuring a separate panel, the add-on panel shall also be included in the offer. (b) General arrangement showing views and details of termination panel, with cable entry particulars, shall be submitted as part of technical bid. (c) Interconnecting the add-on DC termination panel with the main panel, including supply of cables for this purpose, shall be within the scope of vendor.
4.8.10	DC Side Negative Grounding	DC side negative grounding system shall be provided for the PCU. The same shall be indicated in the GA/SLD/Schematics and BOM.

**4.9 AC Output and termination details for 2500kW PCU.**

Vendor shall supply the PCU with the termination requirements on AC side as tabulated below. General arrangement showing views of termination shall be submitted as part of technical bid. Detailed drawings of termination arrangements with bus bar particulars such as positions, dimensions, hole sizes, spacing between holes, support to bus bar, etc shall be submitted within seven days after receipt of purchase order for BHEL approval.

4.9.1	Number of AC outputs	Three phases: R, Y, B terminals
4.9.2	AC cable entry into panel	Bottom entry. Cable supply is within BHEL scope. For each phase, <b>5 runs</b> of 1Cx630 sq.mm aluminium, multi-strand, armoured, XLPE insulation, PVC sheath cable will be used. Final cable selected and cable O.D shall be informed to vendor during



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 12 OF 14**

**COPY RIGHT AND CONFIDENTIAL**

The information on this document is the property of Bharat Heavy Electricals Limited. It must not be used directly or indirectly in anyway detrimental to the interest of the company.

		detailed engineering for selecting suitable cable lugs, glands and termination.
4.9.3	Gland plates	Drilled Gland plates shall be provided with holes to accommodate the cable glands.
4.9.4	Cable glands	Nickel plated brass, double compression type cable glands of reputed make (Make: Comet or any other reputed make) shall be provided by the vendor.  Approval of make and type shall be taken from BHEL before procurement of glands.  PCUs shall be supplied with all glands fixed on the gland plates.
4.9.5	Cable lugs, plain washers, spring washers, bolts and nuts	Similarly, cable lugs, bolts, nuts & plain washers, Zinc coated spring washers shall be provided by the vendor.  AC Cables in BHEL scope shall be Aluminium type. Suitable cable lugs in PCU vendor scope shall be based on the type of busbars being used in PCU :  a) If Copper busbars used, Cu-Al Bi-metallic lugs or Aluminium Lugs with Bi-metallic strips/washers to be provided  b) If Aluminium busbars used, Aluminium lugs to be provided.  Make for lugs: Dowells or any other reputed make with CE/VDE/UL/CSA/BIS.  Approval of make and type shall be taken from BHEL before procurement of these items.  Part no. and qty shall be indicated in the BOM.  PCUs shall be supplied with all these items fixed on the bus bars at their respective positions.
4.9.6	Bus bar design	Tinned Copper or Aluminium busbars shall be provided.
4.9.7	Aux. Transformer taping	Vendor should give provision for tapping Axillary transformer from AC SIDE BUS BAR xxxv/415 volt
4.9.8	In case of separate AC termination panel	In case the AC output terminations are not within the main PCU panel with the vendor design featuring a separate panel, the add-on panel shall also be included in the offer.  General arrangement showing views and details of termination panel, with cable entry particulars, shall be submitted as part of technical bid.  Interconnecting the add-on AC termination panel with the main panel, including supply of cables for this purpose, shall be within the scope of vendor.

**4.10 Panel related parameters**

4.10.1	Structure sheets	Doors and frames - Type of enclosure and size/thickness details of the doors and frames shall be indicated by vendor  Gland plate: Minimum 3mm thk min sheet steel or 4 mm thk non-magnetic
--------	------------------	---



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 13 OF 14**

**COPY RIGHT AND CONFIDENTIAL**  
The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

		material
4.10.2	Bus bars	Busbars shall be of appropriate size to match current rating, based on vertical / horizontal layouts and bus bar orientations. Insulation sleeves (PVC etc.) shall be used wherever necessary. Bus bars (both AC and DC) shall be suitably colour coded.
4.10.6	Fixing of PCU	PCU shall be suitable for fixing on the cable trench channels by the means of tack welding.
4.10.7	Earthing terminals as per relevant standards	Earthing terminals shall be provided using tinned copper / aluminium bars of suitable cross section. Terminals shall be brought out to facilitate external connections.
4.10.8	Insulation clearances	AC side: Phase to Phase / neutral: As per relevant standards DC side: As per relevant standards.
4.10.9	Painting	Epoxy based powder coating. Powder coating shall meet the requirement of IS 13871 Paint shade shall be informed during detailed engineering.
4.10.10	Overall dimensions	Width x Depth x Height in mm shall be indicated in the offer.
4.10.11	Weight	Panel weight shall be indicated in the offer.
4.10.12	Air Flow Requirement (m3/hr)	To be indicated by vendor for each PCU. - HVAC calculations shall be provided by vendor during detailed engg including CFD analysis for ventilation.

**5.0 Testing and inspection**

5.1	<p>Routine tests, as per relevant standards (IEC etc), shall be carried out on the PCUs and shall be witnessed by BHEL &amp; Customer/ Customer authorized third party inspection agency). Vendor shall submit Manufacturing Quality Plan (MQP) and detailed Test Procedure along with drawings for formal approval by customer prior to inspection.</p> <p>Routine tests shall be carried out by vendor on all the PCUs as per customer approved MQP. Following are the minimum tests to be conducted but not limited to:</p> <ul style="list-style-type: none"> <li>(a) HV and IR tests on 100% PCUs.</li> <li>(b) Functional tests</li> <li>(c) Load testing of inverter on 1No. PCU: <ul style="list-style-type: none"> <li>- Verification of inverter performance in its stand alone operational mode with a defined power (up to 100% rated full load power) and DC input voltage (up to max value). All parameters: DC voltage, current, power, grid voltage / current of R,Y,B lines, line frequency, ac output power, ac output energy, power factor, line current, efficiency, THD, etc. to be measured at 25%, 50%, 75% and 100% of the rated nominal power and checked against specified</li> </ul> </li> </ul>
-----	---



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 14 OF 14**

acceptance norms.

- (d) Heat Run Test at rated full load on 1 no. panel
- (e) Protection tests (by direct method or simulation method)
  - Verification of automatic disconnecting and reconnecting of Inverter to the grid, based on rise and fall of heat sink and cabinet temperature with reference to set points.
  - DC Reverse Polarity protection test
  - DC Ground Fault
  - AC and DC Overvoltage
  - Abnormal voltage and frequency

Test reports shall be submitted prior to dispatch of the system to the site.

**COPY RIGHT AND CONFIDENTIAL**

The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.

**6.0 Documents to be submitted after receipt of purchase order**

- 6.1 Following documents shall be submitted for approval within seven days from date of purchase order.
1. GTP/Datasheet
  2. General Arrangement of PCU and other auxiliary equipment, lighting, HVAC details, etc
  3. BOM for complete PCU including all major components of PCU, AC and DC Combiner Panels
  4. Type test reports
  5. Spares List
  6. Manufacturing Quality Plan (MQP)
- Vendor shall proceed with Manufacturing only after final approval of all the listed documents.

**7.0 Documents to be submitted along with consignment**



**PURCHASE SPECIFICATION FOR  
2500 kW OUTDOOR TYPE GRID-CONNECTED POWER  
CONDITIONING UNITS**

**PS 439-1752**

**REV. No. 00**

**PAGE 15 OF 14**

7.1

Following documents shall be submitted at the time of dispatch:

- a. Test reports on individual PCUs
- b. Technical manual with system specifications, installation guidelines, commissioning guidelines, schematic drawings, circuit board overlays, system set points, calibration settings, hardware settings, cable schedule, general arrangement drawings, panel details.
- c. Operation and Maintenance manual including final As Built and tested drgs and datasheet, test reports, Catalogs of individual components, schematic drgs shall be provided (segregated section wise) in both hard copy and soft copy.

**COPY RIGHT AND CONFIDENTIAL**

The information on this document is the property of Bharat Heavy Electricals Limited.  
It must not be used directly or indirectly in anyway detrimental to the interest of the company.